

PicoJet 6000 Driver Patch: Resolves the issue where the Ink Levels do not display in Scribe.

1. Power off the PicoJet Printer and disconnect the USB Cable.
2. Click on Start→ Printers and Faxes, delete the PicoJet 6000 Icon. Right click on the PicoJet Icon and choose Delete.
 - 2A. **SCRIBE 9000 Series Only:** Right click on DO NOT REMOVE Printer and choose Properties. Click on the Advanced Tab. Click the DRIVER drop down menu and select the Rimage Perfect Image Priter PF. Click the Apply button at the bottom of the dialog.
3. Open the PicoJet / PicoJet Driver Patch Folder and run the Setup.exe file.
4. Reboot the computer (Start→shut down→Restart)
5. Click on Start→Printers and Faxes. Choose FILE→Server Properties→Driver Tab. Click on the Picojet 6000 in the list and click the REMOVE button. Now click CLOSE.
6. Power on the PicoJet Printer and reconnect the USB Cable.
7. On the Welcome Wizard window, select No, Not at this time, then click NEXT.
8. Select Install from a specific location, then click Next.
9. Click Browse and navigate to PicoJet / PicoJet Driver Patch / PicoJetDrivers 106 folder. Click OK.
10. Click Next.
11. Select PicoJet 6000 Version 14.0.42320.40D
12. Click Next

Under the Files Needed Dialog:

13. Browse→PicoJetDrivers 106
14. Click OPEN
15. Click OK

Insert Disk Dialog

16. Click OK.
17. Browse→PicoJetDrivers 106
18. Click OPEN
19. Click OK
20. Click FINISH.

21. Perform these steps if ONLY you have a Scribe 9000 Series.

Start→Printers and Faxes
Right Click the DO NOT REMOVE Printer
Select Properties; then select the Advance Tab
Click the Driver Drop Down Menu and select PicoJet 6000.
Click Apply.

22. Printer Properties Window

PicoJet 6000 printer driver is not installed...
Click YES.
Add Printer Wizard appears
Click NEXT.
Select PicoJet 6000
Click NEXT
Click FINISH

Click OK to close, "DO NOT REMOVE printer dialog.
Right click on PicoJet 6000 icon and choose "Set as Default"

Patch is now applied.